

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of: :
SVEN VOIGT et al. :
Serial No. : Examiner:
Filed: :
For: METHOD FOR REGULATING THE :
OPERATING FREQUENCY AND : Art Unit:
MULTIFUNCTIONAL INTEGRATED :
CIRCUIT CHIP OF A FIBER :
OPTIC GYROSCOPE :

Commissioner for Patents
P.O. Box 1450
Alexandria, Virginia 22313-1450

TRANSMITTAL OF SUBSTITUTE SPECIFICATION

Dear Sir:

Transmitted herewith is a (1) Substitute Specification
and (2) marked-up version of the Substitute Specification.

The Substitute Specification was prepared and is filed
for the purpose of correcting the text of the English language
translation of International patent application PCT/EP03/010328
that is submitted herewith. The translation, a literal
translation of the International application that was prepared in
the German language, contains numerous grammatical and
syntactical errors that would unnecessarily complicate the
examination of this application.

10/529707

JC17 Rec'd PCT/PTO 29 MAR 2005

U.S. National Phase of PCT/EP03/010328 Page 2

No new matter is added by the Substitute Specification.

The marked-up version indicates changes from the
literal English language translation of PCT/EP03/010328 by
strikeout (deletions from literal English translation) and
underline (additions to literal English translation).

Respectfully submitted,



Elliott N. Kramsky
Registration 27,812
Attorney for Applicants

Title: METHOD FOR REGULATING THE OPERATING FREQUENCY AND
MULTIFUNCTIONAL INTEGRATED CIRCUIT CHIP OF A FIBER
OPTIC GYROSCOPE

5 Inventors: Sven Voigt
Guenter Spahlinger

BACKGROUND

Field of The Invention

10 The present invention relates to fiber optic
gyroscopes (FOGs). More particularly, this invention
pertains to a method and apparatus for regulating the
operating frequency of a closed loop FOG.

15 Description of the Prior Art

German patent DE 197 53 427 C1 describes a digital
phase modulator for closed loop fiber optic rate-of-rotation
sensors in which the less significant portion of a binary
drive signal supplied by an FOG main controller is converted
20 into an analog signal by means of a relatively low
resolution digital/analog converter to increase resolution.
The analog signal is fed to a dedicated electrode on the
integrated optical chip containing the digital phase
modulator. Resolution can thus be increased e.g. from 8 to
25 approximately 10 bits. The separate dedicated electrode
(or, if appropriate, a separate electrode pair) is assigned
directly to the digital phase modulator.

German patent application 101 30 159.6 discloses a method for avoiding bias errors due to synchronous interference in closed loop fiber-optic gyroscopes by superposing a signal on the demodulated output signal of the FOG detector. Such signal is periodic at the sampling clock rate of the FOG and is applied in the form of a modulation that is added at the digital phase modulator of a multifunctional integrated optical chip. The residue of the added modulation present in the demodulated detector signal is detected and fed to an auxiliary control loop that readjusts the operating frequency so that the added modulation tends toward zero as much as possible.

Implementation of the above method (through the use of a mixed drive signal at the phase modulator of the MIOC), which considerably increases the accuracy of FOGs, has led, in practice to difficulties. Such difficulties relate, in particular, to a conflict of objectives when it is simultaneously attempted to solve digital phase modulator resolution without increasing the structural length of the MIOC other than is described in the abovementioned German patent specification. This is particularly true when the phase modulator is intended to be operated with non-binary drive signals to increase resolution.

25

SUMMARY AND OBJECTS OF THE INVENTION

It is therefore an object of the invention to simplify the regulation of FOG operating frequency.

5 In a first aspect, the invention provides a method for regulating the operating frequency of a fiber optic gyroscope with a closed control loop. The demodulated output signal of the FOG detector, as actual signal, is applied on the one hand to the input of a FOG main
10 controller and, on the other hand, via a gating filter to a VCO that determines the system clock of the FOG. The output signal of the main controller, as modulation signal, is fed to a digital phase modulator formed in a multifunctional integrated optical chip and, for determining and regulating
15 the exact operating frequency of the FOG, a periodic additional modulation signal is superposed on the demodulated detector output signal passing to the gating filter.

20 Such method is characterized in that the additional modulation signal, as analog signal, is fed to separate phase correction electrodes in the multifunctional integrated optical chip.

25 In a second aspect, the invention provides a multifunctional integrated optical chip for a fiber optic

gyroscope in which a phase modulator realized by electrodes arranged parallel to a light guiding path is implemented as at least one functional group.

5 Such multifunctional integrated optical chip is characterized in that, in addition to the phase modulator, an electrode pair arranged parallel to the light guiding path is present for applying a periodic additional modulation signal to a light beam on the light guiding path
10 for the purpose of regulating the operation frequency of the gyroscope.

 The preceding and other features of the invention will be apparent from the detailed description
15 that follows. Such description is accompanied by a set of drawing figures. Numerals of the drawings, corresponding to those of the written description, point to the features of the invention with like numerals referring to like features throughout.

20

BRIEF DESCRIPTION OF THE DRAWINGS

 Figure 1 is a schematic block diagram of the architecture of a FOG with operating frequency regulation in accordance with the invention; and

25

Figure 2 is a simplified plan view of a multifunctional integrated optical chip (MIOC) for realizing the frequency regulating method of the invention.

5 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

Figure 1 is a schematic block diagram of the architecture of a FOG 100 with operating frequency regulation in accordance with the invention. A measurement signal supplied by the detector 10 of the FOG 100 contains
10 rate-of-rotation information. Such signal is demodulated by a FOG demodulator 13 and, as a fiber optic gyroscope with a closed control loop is involved, it is applied to the input of a FOG main controller 14.

15 Figure 2 is a simplified plan view of a multifunctional integrated optical chip (MIOC) 11 for realizing the frequency regulating method of the invention. Referring to both Figures 1 and 2, the FOG main controller 14, inter alia, supplies a preferably non-binary U_n , or
20 resetting signal, at its output side to a digital phase modulator 24 that is formed in the MIOC 11. In mirror-image, in a manner known in theory, this influences the light beams on two light guiding paths L1, L2, produced after a beam splitting at 23 and passing through a measuring
25 coil (not shown) in opposite directions.

In addition to the FOG demodulator 13 and the FOG main controller 14, an additional modulation device 15 is provided, the periodic output signal ϕE of which is superposed on the modulation signal from the FOG main controller and controls, via a gating filter 20, a voltage-controllable oscillator (VCO) 12 that provides the operating clock of the FOG gyroscope system.

According to the invention, the additional modulation signal ϕE passes to an analog section formed in the MIOC 11 and, as best illustrated in Figure 2, is realized by an additional electrode pair 25 that is separate from the digital phase modulator 24. The additional modulator signal ϕE has relatively small amplitude and is periodic at the sampling clock rate. It is thus passed to the additional electrode, or the electrode pair 25 in the example illustrated in Figure 2, and typically, but not exclusively, produces a maximum phase shift of $\pi/32$. This phase shift is sufficient to generate, after demodulation, a signal that controls the VCO 12 via the gating filter 20 in such a way that the desired operating frequency of the FOG system is precisely accomplished. In contrast to the solution described in German patent application 101 30 159.6 the periodic additional modulation signal ϕE for determining gyroscope frequency, is not added to the digital MIOC modulation signal. Rather, it is passed directly to the

additional analog electrode or the electrode pair 25 (i.e.,
to the analog section 22 of the MIOC 11.)

A particular advantage of the invention is that
5 the additional modulation signal ϕE needn't be digitally
converted, obviating the addition of a modulation signal and
additional modulation. Rather, a periodic additional signal
for determining the frequency or regulating the frequency of
the FOG, as analog signal, is fed to separated phase
10 correction electrodes formed in the MIOC.

In the case of a method of the generic type
mentioned in the background, simplification of regulation of
the operating frequency of a FOG is achieved according to
15 the invention by virtue of the fact that a periodic
additional signal for determining the frequency or
regulating the frequency of the FOG, as analog signal, is
fed to separate phase correction electrodes formed in the
MIOC.

20

The MIOC for a FOG in which a phase modulator is
realized by electrodes arranged parallel to a light guiding
path is implemented as at least one functional group. It is
25 suitable for realizing the method of the invention as,
according to the invention, in addition to the phase

modulator, an electrode pair arranged parallel to the light guiding path is present for applying a periodic additional modulation signal to a light beam on the light guiding path to regulate the operation frequency of the gyroscope.

5

An optimized structural size of the integrated optical chip can be achieved when the additional electrode pair is arranged between the digital phase modulator and a beam splitter within the chip.

10

While the invention has been described with reference to its presently preferred embodiment, it is not limited thereto. Rather, the invention is limited only insofar as it is defined by the following set of patent
15 claims and includes within its scope all equivalents thereof.